

# R100H. R250H. Battery-operated tungsten lights... ... with incomparable lighting performance.

Whether hand-held or camera-mounted, Sachtler battery-operated halogen lights offer unsurpassed lighting performance. Your bulb is safely located behind an integrated multicoated protective glass. Removable 4-leaf barndoors can be rotated. Both lights provide for precise focussing in the 1:4 to 1:5.5 range. The handle is equipped with an integrated camera mount and a compartment for your spare bulb. Both lights have a series of LED's customised to the Sachtler Belt-Pack® systems for displaying the remaining battery capacity. The LED's warn users when the battery is low, long before the unit shuts down due to a discharged battery. A sturdy kit case has room for everything you need, anytime you want it.



**Sachtler chargers. Charging batteries easily, quickly, and safely.**



**Using Sachtler Speedcharger. your battery will be up and running again in the shortest possible time. Anywhere in the world.**

## Reporter 100H. For 12V operation.

The Reporter 100H supplies ideal light for CCD cameras. The ergonomically designed 12V/4.5 Ah and 7 Ah Sachtler Belt-Packs® are available to power the tungsten battery lights. Using the 4.5 Ah battery, you can operate the fixture for over 30 minutes. The 7 Ah version powers both camera and fixture for about 30 minutes. If you operate just the fixture alone, the 7 Ah version gives you a running time of about one hour.

You can use the Sachtler Charger 12AS or the Speedcharger to charge your batteries. With its mains and charging indicators, the Charger 12AS is ideal for charging 12V batteries overnight. You are independent and mobile, thanks to automatic mains voltage selection and the charger's light overall weight. Regardless of where you are.



**The Sachtler Charger 12AS - for charging 12V BeltPacks overnight.**

## Reporter 250H. The top of the line in 30V halogen.

Sachtler's Reporter 250H has led the pack in 30V powered tungsten lights for some time. Its wide-area illumination provides for brilliant pictures even with the daylight filter inserted.

Regardless of where you go. When you need a faster option, the microprocessor-controlled Speedcharger can charge your batteries in the shortest possible time. It can be used for 12 and 30V Belt-Pack® batteries without

switching. The microprocessor-controlled speed charger functions automatically, regulates the charging current depending on temperature and present discharge state of the battery, and recovers deep discharged cells. It can charge a 12V battery in just an hour and, once the battery is fully charged, automatically switches to trickle charge mode. 30V Belt-Packs® with 4.5 and 7Ah are usually charged within 2 or 3 hours. For continuous operation,

you can use the PowerPack 300 to directly power the Reporter 250H -just like any other battery-powered light in the Sachtler line -from the mains.



The PowerPack300 power supply turns any battery-operated fixture into a mains-operated one.

Reporter 100H						
Code No.	R100H					
Weight fixture	550g					
Weight barndoor:	150g					
Cable length	2m					
Stand mount:	In camera accessory shoe, 1/4" threaded hole or with accessories					
Socket	GX6.35					
Bulb:	LIF-Code: A1/215, ANSI-Code:FCR					
LCL*:	30mm, z.B. Osram HLX 64625					
Light output in Lux						
With distance in m	2.00	3.00	4.00	5.00	6.00	7.00
Spot 17°:	3440	1530	860	550	380	280
Flood 44°:	630	280	160	100	70	50



Set Reporter 100H4

Reporter 250H						
Code No.	R250H					
Weight fixture	550g					
Weight barndoor:	150g					
Cable length	2m					
Mount:	In camera accessory shoe, 1/4" threaded hole or with accessories					
Socket	GX6.35					
Bulb:	ANSI-Code:EPL					
LCL*:	22mm, z.B. Sylvania 61454					
Light output in Lux						
With distance in m	2.00	3.00	4.00	5.00	6.00	7.00
Spot 20°:	9380	4170	2340	1500	1040	770
Flood 44°:	2500	1110	630	400	280	200