

# DSLR Filmmaking Kit

(Kit-6-CF)

## INSTRUCTION MANUAL



All rights reserved.

No part of this document may be reproduced, stored in a retrieval system, or transmitted by any form or by any means, electronic, mechanical, photocopying, recording, or otherwise, except as may be expressly permitted by the applicable copyright statutes or in writing by the publisher.

#### INTRODUCTION

PROAIM DSLR Kit 6-CF is full production ready filmmaking equipment for prosumer operators to increase the quality and efficiency during production. This shoulder mount camera rig is a dynamic piece of equipment that moves with the operator in a wedding shoot, corporate communications, and POP production to produce 'stills' and videos alike. It consists of versatile camera cage, durable matte box and precise follow focus that are highly configurable and adaptable to the daily demands of production. It embraces the flexibility to accessorize and match production requirements for professional results.

#### IN THE BOX

Please inspect the contents of your shipped package to ensure you have received all that is pictured and listed below.



## **ASSEMBLING YOUR MB-600 MATTE BOX**

• Insert the French flag (top) to your matte box as shown below and then tighten the knob.





 Insert the Side flag to your matte box as shown below and then tighten the knob as shown below.



• Wrap the knicker on conversion ring, as shown in the image



## **Assembling Your DSLR Filmmaking Kit 6-CF**

• Attach rod support system to your tripod plate and tighten with screw driver. Then mount the setup onto your tripod and secure with provided knob.





• Loosening the knob and simple push of provided button on quick release adapter allows you to remove quick release plate. Now attach it to camera base and tighten to secure.





• Slide in the camera setup onto quick release adapter, retighten the knob to ensure slip free connection.





• Now insert 2x 300mm female rods into quick release adapter. Now attach 2x 150mm extension rods to rails and tighten the knobs.





• Loosen the knob on cage bracket in order to insert it to 450mm rails. Using same approach insert another bracket to front of rails and tighten to secure.





• Loosen the knobs on top of cage brackets in order to insert 2x200mm rods into them, retighten to secure.





• Attach top handle to 200mm rods at cage top, retighten the knob to ensure slip free connection.





• Attach straight bracket to back of rail system and tighten the knob. Then insert 2x200mm rods into it and secure with provided knob.





 Now insert shoulder pad to 200mm rails, also attach counter weight and secure with provided knob.





• Attach flexible gear ring to your camera lens and tighten the screw.





• Now insert X9 follow focus to front of rail system, adjust follow focus with your camera and secure.





 You can also attach speed crank to follow focus as per your requirement.



 Now insert MB-600 matte box to front rails, align with lens and secure with the knob as shown below.






• Attach handle setup to front of rods and tighten the knobs to secure it.





**NOTE**: You can tilt handle set as per your requirement by loosen the knob.





# YOUR PROAIM DSLR FILMMAKING KIT 6-CF ALL DRESSED UP AND READY TO GO



(SHOWN WITH OPTIONAL ACCESSORIES)

**Note:** If you wish to use your setup with shoulder rig support rod then please use following sequence of text and pictures to assemble your kit.

### ASSEMBLING YOUR SHOULDER RIG SUPPORT ROD

• Wear your belt around your waist and secure with the help of velcro as shown below.





Attach rod support to waist belt properly. You can adjust the height of your rod support with the help of provided knobs.





Attach the rod support to your shoulder rig via 15mm rod adapter .This set up allows you to have fatigue free and long comfy shoots.





YOUR DSLR FILMMAKING KIT 6-CF WITH ROD SUPPORT ALL DRESSED UP AND READY TO GO



#### WARRANTY

We offer a one year warranty for our products from the date of purchase.

We will repair or replace your product, free of charge, in the event of a defect in materials or craftsmanship obtained during normal use or handling based on the user manual. Please note that we will not cover any shipping costs for returning the product to us. If any VAT or import duties are applied to the return, we will also charge these costs to the customer.

The warranty does not include, by the way of example, damage caused by products that we do not supply or from mishandling in transit, accident, misuse, neglect, lack of care of the product, or service by anyone other than our company.

We are not liable for incidental or consequential damages resulting from the use of the unit or occurring due to any breach of this warranty.

Replacement parts of the product will be provided at nominal cost (covering the cost price of the replacement parts only) to the customers after the Warranty Period has expired. We will cover the complete cost of sending replacement parts within the warranty period. After that, Nominal cost of the product & Actual shipping cost will be charged.

Do not send the unit to us without first getting a response and getting the approval to send back the item.

In case of any kind of dissatisfaction, we urge you to Contact us immediately and we shall do our best to help you out.

For any other assistance you can reach us via email.